

3.35 Charging message indicators - Code 11101100

8	7	6	5	4	3	2	1
H	G	F	E	D	C	B	A

Bits BA: Tariff indicator current tariff

00: Current rate not present

01: Current rate present - Rate expressed in deciseconds

10: Current rate present - Rate expressed in centiseconds

11: Current rate present - Rate expressed in milliseconds

Bits DC: Tariff indicator next tariff

00: Time indicator and next rate not present

01: Time indicator and next rate present - rate expressed in deciseconds

10: Time indicator and next rate present - rate expressed in centiseconds

11: Time indicator and next rate present - rate expressed in milliseconds

Bits E TO H: Spare

3.36 Current rate/Next rate

8	7	6	5	4	3	2	1
H	G	F	E	D	C	B	A
P	O	N	M	L	K	J	I

Tariff rates expressed according to charging message indicators (2 bytes).

TTS	ISUP FORMATS & CODES	710-00128-AAAA DS	ED 2	28 JULY 1993
-----	----------------------	-------------------	------	--------------

3.37 Time indicator - Code 11101111

8	7	6	5	4	3	2	1
H	G	F	E	D	C	B	A

H G F E D C B A

0 0 0 0 0 0 0 0

spare

0 0 0 0 0 0 0 1

00.30 H

0 0 0 0 0 0 1 0

01.00 H

.

.

.

.

0 0 1 1 0 0 0 0

24.00 H (midnight)

.

.

.

.

spare

TABLE 24/Q.763

Message type: User-to-user information

Parameter	Reference section	Type	Length (octets)
Message type	2.1	F	1
User-to-user information	3.34	V	5-37

TABLE msg A

Message type: Backward charging message (BCM)

Parameter	Reference section	Type	Length (octets)
Message type	2.1	F	1
Charging message indicators	3.35	F	1
Current rate	3.36	F	2
Time indicator	3.37	F	1
Next rate	3.36	F	2